

Remote Keypad



Control Panel



The new CP8 Control Panel from **eurowsec** is the latest and most innovative domestic panel in the market today. This has been specifically designed in co-ordination with electrical installers and also with homeowners to produce an end product that offers a host of features, simplicity of installation, simplicity of use and an advantageous physical design.

- 8 Fully programmable zones.
- 9 User Codes.
- 4 Different set types - Full set & Part set 1, 2 & 3.
- Tamper indication for Keypad(s), End Station, Bell Box & Detectors.
- Up to 4 Remote Keypads.
- 80 Event memory allowing identification of user who unset.
- System set via strobe confirmation.
- Engineer/User reset for 24hr.
- Engineer/User reset.
- Alert keys for Alarm/Fire on Keypad.
- Easy setting facility.
- Programmable output.
- Non Volatile Memory (NVM).

The eurowsec CP8 is the ultimate user friendly panel, giving the user the flexibility to allow the security system to blend in with their décor and surroundings whilst offering the ultimate protection.

- Superior eye catching keypad with covering flap.
- 9 user code options that can be easily added or deleted.
- 4 different set options to allow a full set and 3 different part sets, for example when the children are in bed.
- Quick easy setting option on the keypad.
- Up to 4 keypads can be fitted from the panel each with alert operation by pressing keys 1 & 3.
- The eurowsec CP8 Control Panel offers the complete flexible security option with the ultimate simple user operation.

power input	230v a.c +/- 10% @50Hz
no. zones	8
max loop resistance	2K Ohms
loop delay time	300 milliseconds
fuses	
mains fuse	200mA slow blow
f2 misc fuse	250mA quick blow
f1 system fuse	1A quick blow
low voltage output	13.8v (typical) Regulated
power supply rating	1A
battery sizes	12v 1.2Ah, 2.0Ah, 3.0Ah & 7.0Ah

quiescent current	
control panel	50mA
rkp	40mA
complies with	BS 4737 part 1 CE Tested
conforms with	EMC Directive 89/336/EEC LVD Directive 72/23/EEC
dimensions	
control panel	W247mm H192mm D73
rkp	W90mm H113mm D23mm
log size	80 Events (accessed via Engineer Code)
default codes	
engineer	1234
master user	5678
number of codes	1 Engineer 9 Users on preset level
display type	LED
method of operation	Remote Keypad(s)



Supplied By

